

Evaluation of a Low Frequency Clock Oscillation Circuit

SSP-T7 7.0pF with uPD78F1014GC-16BT [LQFP(14x14) 0.5mm pitch]

Measurement conditions : 3.0V





Model :SSP-T7
 Frequency :Fo=32.768kHz
 Frequency tolerance :dF/Fo= +/-20x10⁶
 Load capacitance :CL=7.0pF
 Equivalent series resistance :R1=65kΩ max
 Max. drive level :DL=1μW max
 Level of drive :DL=0.1μW typ

FEATURES

- 1.Ultra thin type with 1.4mm Max.
- 2.SMD type suitable for automatic & high density surface mounting.
- 3.Plastic mold package containing highly reliable tubular type quartz crystal.
- 4.Excellent shock and heat resistance.
- 5.Cellular phones,PDA,Radio communication equipment, Portable applications etc.

RECOMMENDED SOLDERING PATTERN



	REGVDD	Oscillation mode
Mode 1	2.4V	Normal (*1)
Mode 2	1.8V	

***1 ; Normal current consumption mode**

MODEL:SSP-T7 7.0pF with uPD78F1014GC at 25°C

Key specifications	Mode 2	Mode 1	Remarks
Current control resistance : Rd (kΩ)	0	0	Control drive level & secure phase margin
Capacitance at gate : Cg (pF)	10	10	Optimal capacitance in response to CL
Capacitance at drain : Cd (pF)	10	10	(CL = Cd // Cg + stray capacitance)

Circuit characteristics (at 25°C)	Mode 2	Mode 1	Remarks
Matching Accuracy : df / f (x10 ⁻⁶)	2.7	2.9	Frequency offset volume at specified Vdd
Voltage Fluctuation : +/-df / V (x10 ⁻⁶)	0.0	0.0	Vdd +/-10% (Standard operating voltage range)
Drive Level : DL (μW)	0.02	0.02	DL=Ix ² Re < 1x10 ⁻⁶ W, Re=R1(1 + Co / CL) ²
Negative resistance : - RL (kΩ)	668	668	5 times larger than R _{1MAX}
Oscillation allowance : M (times)	10	10	Judgmental standard of oscillation stability
Current consumption : Id (nA)	419	418	Cd charge current, Id = ωCd*Vd < 500nA
Voltage of oscillation start : Vstrat (V)	1.72	1.61	
Voltage of oscillation stop : Vstop (V)	1.59	1.59	
Oscillation start up time : Ts (sec)	0.83	0.83	Time to reach 90% of output level, Ts < 1.5sec

Temperature characteristics of circuit	Mode 2	Mode 1	Remarks	
at -40°C	Variation : df / T (x10 ⁻⁶)	-132	-132	Typ.Tp=25°C (K = -3.5x10 ⁻⁸ / °C ²)
at +85°C	Variation : df / T (x10 ⁻⁶)	-138	-138	Typ.Tp=25°C (K = -3.5x10 ⁻⁸ / °C ²)

The above mentioned value is only for your reference. The value is for the arbitrary samples and does not guarantee the product's characteristics. Please review and check above parameters at customer's end.

Seiko Instruments USA Inc.

2990,West Lomita Blvd., Torrance, CA 90505, U.S.A
 Telephone :+1 310-517-7771 Facsimile :+1 310-517-7792
 Email :info@siu-la.com

Seiko Instruments GmbH

Siemensstrasse 9,D-63263 Neu-Isenburg,Germany
 Telephone :+49-6102-297-0 Facsimile :+49-6102-297-320
 Email :info@seiko-instruments.de

Seiko Instruments Inc.

1-8,Nakase,Mihama-ku,Chiba-shi,Chiba 261-8507,Japan
 Facsimile :+81-43-211-8030
 E-mail :component@sii.co.jp



We value the "takumi" spirit.

Seiko Instruments Inc.

Phone:+81-43-211-1207(Direct)

Evaluation of a Low Frequency Clock Oscillation Circuit







SSP-T7 7.0pF with uPD78F1014GC-16BT [LQFP(14x14) 0.5mm pitch]

Measurement conditions : 3.0V



Normal current consumption mode

Test Data at 25°C



Evaluation of a Low Frequency Clock Oscillation Circuit







SSP-T7 7.0pF with uPD78F1014GC-16BT [LQFP(14x14) 0.5mm pitch]

Measurement conditions : 3.0V



Normal current consumption mode

Test Data : Temperature characteristics



Evaluation of a Low Frequency Clock Oscillation Circuit


SSP-T7 7.0pF with uPD78F1014GC-16BT [LQFP(14x14) 0.5mm pitch]

Measurement conditions : 3.0V



Normal current consumption mode

Referential components layout(see Figure 1)



78K0R/Kx3-L series

**78K0R/KF3-L*

uPD78F1010

uPD78F1011

uPD78F1012

**78K0R/KG3-L*

uPD78F1013

uPD78F1014

MODEL:SSP-T7 7.0pF with uPD78F1014GC at 25°C

AMPHS1	AMPHS0	Oscillation mode selection
0	0	Low consumption oscillation mode.(default) ; Id=230nA typ.
0	1	Normal consumption oscillation mode. Id=410nA typ.
1	0	Extremely low consumption oscillation mode. *N/R
1	1	oscillation mode. *N/R

***N/R: Not recommended.(underestimated gain at 7.0pF)**

Figure 1 Referential components layout

Notes for Board Design

When using a crystal resonator, place the resonator and its load capacitors as close as possible to SUB_in and SUB_out pins.

Other signal lines should be routed away from the resonator circuit to prevent induction from interfering with correct oscillation (see figure 2).




Figure 2 Example of Incorrect Board Design

Remark When using the subsystem clock, insert a resistor, Rd, in series on the SUB_out side.

Evaluation of a Low Frequency Clock Oscillation Circuit

SSP-T7 7.0pF with uPD78F1014GC-16BT [LQFP(14x14) 0.5mm pitch]

Measurement conditions : 3.0V



Normal current consumption mode

[Evaluation Sample at 25°C]

SAMPLE	No.	CL(pF)	Fo(Hz)	fr(Hz)	R1(kΩ)	Co(pF)	C1(fF)	Q(k)
SSP-T7	1	7.0	32768.00	32763.63	37.8	0.90	2.107	61.0
	2	7.0	32768.03	32763.64	39.4	0.91	2.118	58.2
	3	7.0	32768.11	32763.76	42.6	0.91	2.100	54.3

[IC Test Data : IC sample Rd=0Ω,Cg=10pF,Cd=10pF at 25°C]


MODE	IC sample	Fosc(Hz)	df / f(x10 ⁻⁶)	DL(μW)	M(times)	XT2(Vpp)	Id(nA)	Vstart(V)	Ts(sec)
Mode 1	Sample 1	32768.08	2.7	0.03	9	0.93	441	1.58	0.95
	Sample 2	32768.08	2.6	0.03	10	0.89	420	1.58	0.94
	Sample 3	32768.09	2.9	0.02	10	0.89	418	1.59	0.83
	Sample 4	32768.06	2.1	0.02	11	0.81	385	1.59	0.74
	Sample 5	32768.05	1.9	0.02	10	0.81	384	1.59	0.75

[IC Test Data : IC sample Rd=0Ω,Cg=10pF,Cd=10pF at 25°C]

MODE	IC sample	Fosc(Hz)	df / f(x10 ⁻⁶)	DL(μW)	M(times)	XT2(Vpp)	Id(nA)	Vstart(V)	Ts(sec)
Mode 2	Sample 1	32768.07	2.5	0.03	9	0.93	442	1.67	0.95
	Sample 2	32768.07	2.4	0.03	10	0.89	420	1.68	0.94
	Sample 3	32768.08	2.7	0.02	10	0.89	419	1.72	0.83
	Sample 4	32768.05	1.9	0.02	11	0.81	386	1.69	0.74
	Sample 5	32768.05	1.7	0.02	10	0.81	384	1.70	0.75

Remark (see figure 3)

$$F_o = f_r \times \left\{ \frac{C_1}{2 \times (C_o + C_L)} + 1 \right\} \text{ (Hz)}$$



Fo : Load resonance frequency
fr : Resonance frequency
R1 : Motional resistance
C1 : Motional capacitance
Co : Shunt capacitance
CL : Load Capacitance


Figure 3 Equivalent circuit of crystal unit, and CL**Remark (see figure 4)**

Approximate formula of the load capacitance of the circuit CL,

$$C_L = C_g \times C_d / (C_g + C_d) + C_s \text{ (pF)}$$

$$C_s = C_{gs} \times C_{ds} / (C_{gs} + C_{ds}) + C_{os} \text{ (pF)}$$

where Cs(=1.5 to 2.5pF) stands for stray capacitance of the circuit.



Cos : X1_X2 Stray capacitance
Cgs : X1_Vss Stray capacitance
Cds : X2_Vss Stray capacitance

Figure 4 Stray capacitance Cos,Cgs,Cds of the circuit

Resonator circuit constants differ depending on the resonator element, stray capacitance in its interconnecting circuit, and other factors. Suitable constants should be determined in consultation with the resonator element manufacturer.



Evaluation of a Low Frequency Clock Oscillation Circuit







SSP-T7 7.0pF with uPD78F1014GC-16BT [LQFP(14x14) 0.5mm pitch]

Measurement conditions : Vcc=(1.6V) to (6.0V) at 25°C



Normal current consumption mode

Referential Data(1) : Voltage characteristics



Evaluation of a Low Frequency Clock Oscillation Circuit







SSP-T7 7.0pF with uPD78F1014GC-16BT [LQFP(14x14) 0.5mm pitch]

Measurement conditions : Vcc=(1.6V) to (6.0V) at 25°C



Normal current consumption mode

Referential Data(2) : Voltage characteristics



Evaluation of a Low Frequency Clock Oscillation Circuit









SSP-T7 7.0pF with uPD78F1014GC-16BT [LQFP(14x14) 0.5mm pitch]

Measurement conditions : Vdd=3.0V at 25°C



Normal current consumption mode

Referential Data(4) : Load capacitance characteristics



Evaluation of a Low Frequency Clock Oscillation Circuit

SSP-T7 7.0pF with uPD78F1014GC-16BT [LQFP(14x14) 0.5mm pitch]

Measurement conditions : V_{dd}=3.0V at 25°C



Normal current consumption mode


Referential Data(5) : Selection of XT1 oscillation mode and recommended load capacitance

For 78K0R/Kx3-L series

XT1 oscillation circuit has the function (via software) to select the XT1 oscillation mode.

The XT1 oscillation mode can be switched over just one time among normal oscillation (Normal), low consumption oscillation (Low), and "extremely low consumption oscillation" mode (E-Low).

Correlations between the oscillation mode selection of XT1 oscillation circuit and the recommended load capacitance for a resonator are shown in Table 1 for safety use.



SSP-T7 series

SSP-T7-FL CL=3.0pF, 3.7pF, 4.4pF, 6.0pF and SSP-T7-F CL=7.0pF, 9.0pF

Table 1 Oscillation mode selection of XT1 oscillation circuit and load capacitance for a resonator

XT1 oscillation mode selection	Recommended circuit constant and load capacitance for a resonator				
	C _g =3pF, C _d =2pF	C _g =4pF, C _d =3pF	C _g =9pF, C _d =8pF	C _g =10pF, C _d =10pF	C _g =15pF, C _d =15pF
E-Low Extremely low consumption oscillator	SSP-T7-FL 3.0pF <i>Id=65nA typ</i> <i>RL=-990kΩ typ</i> <i>Ts=0.75sec typ</i>	SSP-T7-FL 3.7pF <i>Id=80nA typ</i> <i>RL=-730kΩ typ</i> <i>Ts=0.85sec typ</i>	SSP-T7-FL 6.0pF <i>Id=120nA typ</i> <i>RL=-340kΩ typ</i> <i>Ts=1.60sec typ</i>	<i>Not recommended.</i>	<i>Not recommended.</i>
Low Low consumption oscillator	<i>Not recommended.</i>	<i>Not recommended.</i>	SSP-T7-FL 6.0pF <i>Id=210nA typ</i> <i>RL=-500kΩ typ</i> <i>Ts=1.05sec typ</i>	SSP-T7-F 7.0pF <i>Id=230nA typ</i> <i>RL=-410kΩ typ</i> <i>Ts=1.30sec typ</i>	<i>Not recommended.</i>
Normal Normal oscillation	<i>Not recommended.</i>	<i>Not recommended.</i>	SSP-T7-FL 6.0pF <i>Id=370nA typ</i> <i>RL=-835kΩ typ</i> <i>Ts=0.70sec typ</i>	SSP-T7-F 7.0pF <i>Id=410nA typ</i> <i>RL=-660kΩ typ</i> <i>Ts=0.85sec typ</i>	SSP-T7-F 9.0pF <i>Id=500nA typ</i> <i>RL=-380kΩ typ</i> <i>Ts=1.40sec typ</i>

NEC MPU 78K0R/Kx3-L series

- 78K0R/KF3-L; uPD78F1010, uPD78F1011, uPD78F1012
- 78K0R/KG3-L; uPD78F1013, uPD78F1014

